Flat Position



Use the provided alcohol wipe to clean the area where the unit will be placed. Allow it to dry completely.



Pull the battery tab from the bottom of the Zips alarm unit.



Peel the adhesive from the bottom of the alarm unit.



Optional:

If the alarm unit will be powered, plug the power cable into the alarm unit.



Place the alarm unit into the shell. Make sure that the port is oriented in the shell as shown.



6 Place the base plate into the shell as shown.




Rotate the base plate into position, so that the screw hole is visible.



8 Insert the provided screw into the screw hole.










Peel the clear film from the adhesive.



Optional:
If the power cable was installed in the alarm unit, route the cable through a hole or slot in the fixture.



With the sensor port facing away from the customer position, place the unit onto the fixture and apply pressure for at least 10 seconds.



Optional:

If the alarm unit will be powered, connect the power cable from the alarm unit to the PS512 power supply. Plug the PS512 into a power outlet.



Use a charged and coded OneKEY to disarm the alarm unit when needed.



Angled Position



Use the provided alcohol wipe to clean the area where the unit will be placed. Allow it to dry completely.



Pull the battery tab from the bottom of the Zips alarm unit.



Peel the adhesive from the bottom of the alarm unit.



Optional:

If the alarm unit will be powered, plug the power cable into the alarm unit.



Place the alarm unit into the shell. Make sure that the port is oriented in the shell as shown.



6 Place the base plate into the shell as shown.




Rotate the base plate into position, so that the screw hole is visible.



Align the angle adapter plate with the unit as shown.









Insert the provided screw into the screw hole.



Tighten the screw with a Philips head screwdriver.



Peel the clear film from the adhesive.



Optional:

If the power cable was installed in the alarm unit, route the cable through a hole or slot in the fixture.



With the sensor port facing away from the customer position, place the unit onto the fixture and apply pressure for at least 10 seconds.



Optional:

If the alarm unit will be powered, connect the power cable from the alarm unit to the PS512 power supply. Plug the PS512 into a power outlet.



Use a charged and coded OneKEY to disarm the alarm unit when needed.

